

TR-285

Broadband Copper Cable Models

Issue: 1 Corrigendum 1
Issue Date: November 2015

Notice

The Broadband Forum is a non-profit corporation organized to create guidelines for broadband network system development and deployment. This Broadband Forum Technical Report has been approved by members of the Forum. This Broadband Forum Technical Report is not binding on the Broadband Forum, any of its members, or any developer or service provider. This Broadband Forum Technical Report is subject to change, but only with approval of members of the Forum. This Technical Report is copyrighted by the Broadband Forum, and all rights are reserved. Portions of this Technical Report may be copyrighted by Broadband Forum members.

THIS SPECIFICATION IS BEING OFFERED WITHOUT ANY WARRANTY WHATSOEVER, AND IN PARTICULAR, ANY WARRANTY OF NONINFRINGEMENT IS EXPRESSLY DISCLAIMED. ANY USE OF THIS SPECIFICATION SHALL BE MADE ENTIRELY AT THE IMPLEMENTER'S OWN RISK, AND NEITHER the Forum, NOR ANY OF ITS MEMBERS OR SUBMITTERS, SHALL HAVE ANY LIABILITY WHATSOEVER TO ANY IMPLEMENTER OR THIRD PARTY FOR ANY DAMAGES OF ANY NATURE WHATSOEVER, DIRECTLY OR INDIRECTLY, ARISING FROM THE USE OF THIS SPECIFICATION.

Broadband Forum Technical Reports may be copied, downloaded, stored on a server or otherwise re-distributed in their entirety only, and may not be modified without the advance written permission of the Broadband Forum.

The text of this notice must be included in all copies of this Broadband Forum Technical Report.

Issue History

Issue Number	Approval Date	Publication Date	Issue Editor	Changes
1	23 February 2015	16 March 2015	Andre Holley	Original
Corrigendum 1	9 November 2015	11 November 2015	Andre Holley TELUS	Original

Comments or questions about this Broadband Forum Technical Report should be directed to help@broadband-forum.org.

Editor	Andre Holley	TELUS Communications	andreholley@telus.net
Physical Layer Transmission WA Directors	Les Brown	Huawei	lesbrown@sympatico.ca
	Massimo Sorbara	Ikanos Communications	msorbara@ikanos.com

TABLE OF CONTENTS

EXECUTIVE SUMMARY.....5

1 PURPOSE AND SCOPE6

1.1 PURPOSE.....6

1.2 REFERENCES6

2 TECHNICAL REPORT IMPACT7

2.1 ENERGY EFFICIENCY7

2.2 IPV67

2.3 SECURITY7

2.4 PRIVACY.....7

3 UPDATE SECTION A.1. PATCH, A.1.1 TRANSFER FUNCTION.....8

4 UPDATE SECTION A.2 MULTI-PAIR CABLE, A.2.1 TRANSFER FUNCTION8

5 UPDATE SECTION A.3 ISOLATED DROP WIRE, A.3.1 TRANSFER FUNCTION.....9

Executive Summary

This corrigendum updates the Cable transfer function equations in TR-285.

1 Purpose and Scope

1.1 Purpose

The purpose of this corrigendum is to align the transfer function definition in TR-285 with that used in ITU-T G.993.2.

1.2 References

The following references are of relevance to this Technical Report. At the time of publication, the editions indicated were valid. All references are subject to revision; users of this Technical Report are therefore encouraged to investigate the possibility of applying the most recent edition of the references listed below.

A list of currently valid Broadband Forum Technical Reports is published at www.broadband-forum.org.

Document	Title	Source	Year
RFC 2119	Key words for use in RFCs to indicate Requirement Levels [2]	BBF	1997
ATIS-0600024	Multiple-Input Multiple Output Crosstalk Channel Model	ATIS	2009
ITU-T G.9701	Telecommunications Standardization Draft Recommendation Study Group 15 TD 159 Rev, 2 (PLEN/15) Fast Access to Subscriber Terminals (FAST) – Physical layer specifications.	ITU-T	2014
ITU-T G.993.2	Very high speed digital subscriber line transceivers 2 (VDSL2)	ITU-T	2006
ETSI TS 101 271, V1.2.1	Access Terminals Transmission and Multiplexing (ATTM); Access transmission system on metallic pairs. Very High Speed digital subscriber line systems. (VDSL2)	ETSI	Jan. 2013

2 Technical Report Impact

2.1 Energy Efficiency

TR-285i1c1 has no impact on energy efficiency.

2.2 IPv6

TR-285i1c1 has no impact on IPv6.

2.3 Security

TR-285i1c1 has no impact on security.

2.4 Privacy

Any issues regarding privacy are not affected by TR-285i1c1.

3 Update Section A.1. Patch, A.1.1 Transfer Function

Use the nomenclature:

Patch Section length = “ d_p ”
Source impedance = “ Z_{soP} ”
Load impedance of “ Z_{LP} ”

Compute

$$\gamma = \alpha + j\beta = [Z_s(j\omega) Y_p(j\omega)]^{0.5}$$
$$Z_0 = [Z_s(j\omega) / Y_p(j\omega)]^{0.5}$$

The Patch Section transfer function, “ H_p ,” is then given by the following equation:

$$H_p = 2 * [Z_{inP} / (Z_{inP} + Z_{soP})] T_p$$

[NOTE – The Isolated Drop Wire transfer function definition is associated with a two port network, normalized to the reference load impedance \$Z_{LW}\$ \(see clause 11.4.1.1.1 of \[ITU-T G.993.2\]\). The formula assumes that \$Z_{LW}\$ and \$Z_{soW}\$ are equal.](#)

Here:

$$T_p = [\cosh(\gamma d_p) + (Z_0 / Z_{LP}) \sinh(\gamma d_p)]^{-1}$$

Z_{inP} = The Input Impedance of the Patch Section– which follows in Section A.1.2

4 Update Section A.2 Multi-Pair Cable, A.2.1 Transfer Function

Use the nomenclature:

Multi-Pair Cable Section length = “ d_D ”
Source impedance = “ Z_{soD} ”
Load impedance of “ Z_{LD} ”

Compute

$$\gamma = \alpha + j\beta = [Z_s(j\omega) Y_p(j\omega)]^{0.5}$$
$$Z_0 = [Z_s(j\omega) / Y_p(j\omega)]^{0.5}$$

The Multi-Pair Cable transfer function, “ H_D ,” is then given by the following equation

$$H_D = 2 * [Z_{inD} / (Z_{inD} + Z_{soD})] T_D$$

[NOTE – The Isolated Drop Wire transfer function definition is associated with a two port network, normalized to the reference load impedance \$Z_{LW}\$ \(see clause 11.4.1.1.1 of \[ITU-T G.993.2\]\). The formula assumes that \$Z_{LW}\$ and \$Z_{soW}\$ are equal.](#)

Here:

$$T_D = [\cosh(\gamma d_D) + (Z_0 / Z_{LD}) \sinh(\gamma d_D)]^{-1}$$

Z_{inD} = The Input Impedance of the Multi-Pair Cable– which follows in Section A.2.2

5 Update Section A.3 Isolated Drop Wire, A.3.1 Transfer Function

The Isolated Drop Wire transfer function, “ H_W ,” is then obtained by the following equation

$$H_W = 2 * [Z_{inW} / (Z_{inW} + Z_{soW})] T_w$$

[NOTE – The Isolated Drop Wire transfer function definition is associated with a two port network, normalized to the reference load impedance \$Z_{L,W}\$ \(see clause 11.4.1.1.1 of \[ITU-T G.993.2\]\). The formula assumes that \$Z_{L,W}\$ and \$Z_{soW}\$ are equal.](#)

Here:

$$T_W = [\cosh(\gamma d_W) + (Z_0 / Z_{L,W}) \sinh(\gamma d_W)]^{-1}$$

Z_{inW} = The Input Impedance of the Isolated Drop Wire – which follows in Section A.3.2

End of Broadband Forum Technical Report TR-285i1c1